


## **BIG CARROUSEL**






## **ECOFRY SYSTEM - The Perfect Cycle**

- **1. Frying -** protects oil from light, water and oxygen, extending it's useful lifespan.
- **2. Drained, golden & crispy -** with extraction of: Evaporated water, oil and excess solid particles.
- **3. Extraction -** perfzctly cooked product is extracted through the chute into the waiting containers.



# **BIG CARROUSE**



#### **Dimensions**

Big Carrousel			
Height	37.0"	942 mm	
Width	29.9"	760 mm	
Depth	22.4"	570 mm	
Depth with tray	29.5"	750 mm	
Weight	210 lbs.	95 Kg	
Weight packed	231 lbs.	105 Kg	
Technical Specifications			
Oil capacity	10 litres		
Hopper load	4 zone + 2 cooking	500-800g	
Hourly production	Up to	33 Kg**	
Controls	10,1" Touch screen	21 pre-set times	
Wall air clearance (Big Carrousel not intended for built-in installations)			
Top (to allow loading)	12"	3000 mm	
Sides	6"	150 mm	

Big Carrousel installed in enclosed areas with limited or no access may invalidate

Avoid installing the Big Carrousel directly next to heat sources (ovens, grills etc.) or

air conditioning outlets. Exhaust air is vented from the top of the unit.

\*\*Hourly production based on 6mm French fries easy to fry. Oil type, oil age, cooking temperature and product starting temperature will effect cook times and hourly

## **Electrical specification - Three Phase**

Big Carrousel		
Voltage	380 VAC	(00)
Frequency	50 - 60 Hz	
Circuit breaker	16 amp	
Plug/socket	IEC TRIF , 16 amp 3-pin +N +E socket	
Max input	7,800 Watts	

## Cleaning schedule

- Cooking oil should be drained and filtered daily.
- The frying chamber should be removed, stripped and completely cleaned at least once per week.
- Condensation tank should be drained at least once per week and flushed out once a month.
- Condensation filter needs to be flushed once a month.
- Panel grease filter needs to be cleaned every six months.
- Activated carbon cylindrical filter must be replaced at least every 12 months.

Continuing research results in steady improvements; therefore, these specifications are subject to change without notice.

